8w Exit Box



| Specification | | | |
|---------------------------|--|-------------|--|
| | Non Maintained | Maintained | |
| Light Source | 1 x 8 watt T5 | | |
| Construction | Steel Body Painted White (RAL9003)/ Opal Diffuser c/w Running Man Legend | | |
| Light Output Mains | N/a | 400 lm | |
| Light Output Emergency | 100 lm | 100 lm | |
| Battery | 2.4 Volt 4Ah Nicad | | |
| Charge Current | 250mA Nominal | | |
| Input Voltage | 230 Volt AC +10% -6% 50 Hz | | |
| Power | 9 VA (Max) | 21 VA (Max) | |
| Size | 390mm x 192mm x 60mm | | |

A traditional slim metal Exit sign, with a viewing distance of 32 meters. Although a basic exit, this luminaire has clean lines and a generous downlight panel providing floor level illumination. Available in white, brass and chrome. Supplied with legend.

SPECIFICATION

Emergency Exit box constructed from steel body painted white (RAL9003) complete with screen printed legend. Supplied with lamp, as Preslite 8w Exit Box Range.

ORDER CODES

| Maintained | ZE318M |
|----------------------|---------------------|
| Slave (24v/50v/110v) | ZE38/(24v/50v/110v) |
| Self Test | /ST |
| Brass | /BR |
| Chrome | /CH |

